

## Saving and Recalling Panel Setups

### PANEL SETUPS

PANEL SETUPS

Recall  
Save

TO SETUP1


TO SETUP2

TO SETUP3

TO SETUP4

to Card  
Fipy or HDD

PANEL  
SETUPS

Press  to access the menus used for saving or recalling configurations — panel setups — to non-volatile memory or floppy disk, or to memory card or portable hard disk (HDD) depending on options installed.

#### Recall Save

To choose to save a panel setup or recall one already saved. When **"Save"** is selected, as *shown here*, the "TO SETUP" menus appear. While when **"Recall"** is chosen, the "FROM SETUP" menus, *shown overleaf*, appear.

#### TO SETUP 1 ...2 ...3 or ...4

For saving any of four possible setups.

#### to Card, Fipy or HDD

For saving a setup to floppy, memory card, or hard disk, depending on options.

PANEL SETUPS

Recall Save
FROM SETUP1 04-JUN-1996 09:40:43
FROM SETUP2 24-MAY-1996 14:25:00
FROM SETUP3 01-APR-1996 16:00:11
FROM SETUP4 24-MAY-1996 14:38:12
FROM DEFAULT SETUP
From Card Flpy or HDD

### Recall or Save

To select for saving or recalling a panel setup. When "Save" is selected, *as shown on the previous page*, the "TO SETUP" menus appear. While when "Recall" is chosen, *as shown here*, the "FROM SETUP" menus appear.

### FROM SETUP 1 ...2 ...3 or ...4

For recalling any of four possible saved setups. In the example shown here, all four possible setups have been stored. When no setup has been stored, that menu will indicate "Empty".

### FROM DEFAULT SETUP

To choose a default setup, already stored in the scope.

### from Card, Flpy or HDD

For accessing the secondary "RECALL SETUPS" menu to recall a setup stored on floppy, card or portable hard disk, depending on the options installed.

---

## RECALL SETUPS

RECALL SETUPS

From

Card **Flopy**

HDD

Directory:  
LECRDY\_1.DIR

10-OCT-96  
09:52:12  
Size 3403

DO RECALL  
ONE.PNL

File

**ONE** PNL

ZERO PNL

### from

For selecting to recall a setup from floppy, or card or portable hard disk, depending on the options installed and the medium on which the desired setup is stored.

### DO RECALL

To perform the recall of the setup selected in the "File" menu (*see below*).

### File

For selecting the stored setup, using the attributed menu knob.